

user manual  
inside


# zameL

ZAMEL Sp. z o.o.  
43-200 Pszczyzna, ul. Zielona 27  
tel.: +48 32 210 46 65; fax: +48 32 210 80 04  
e-mail: export@zamel.pl  
www.zamel.com

## BATTERY-OPERATED 4-CHANNEL RADIO TRANSMITTER RNP-22

- 4-input (4-channel) radio transmitter
- remote control of EXTA LIFE system receivers
- capable of independent control of up to four circuits (receivers)
- encrypted RF transmission
- battery-operated
- small dimensions enabling installation under traditional mounting equipment
- long operating range (up to 300 m in open areas)

The RNP-22 transmitter enables wireless control of EXTA LIFE system receivers. It is designed to implement such functions as turning on/off lighting, adjusting illumination, opening/closing roller shutters and garage doors. The transmitter is designed for installation in flush mounting boxes (min. Ø60 mm) under existing equipment. It enables the use of electrical installation equipment from any manufacturer and causes no restrictions to the interior design and nature. The transmitter is battery-operated, so it can be installed at any location.



3 V DC (CR2032); IP20  
Net weight: 0,02 kg  
PN-ETSI EN 300 220-1  
PN-ETSI EN 300 220-2

ZAMEL Sp. z o.o. declares that the device complies with principal requirements and other applicable rules of the 2014/53/UE Directive.

Registered design © ZAMEL

Made in Poland



The symbol means selective collecting of electrical and electronic equipment. It is forbidden to put the used equipment together with other waste.



## zameL



- easy installation in a Ø60 mm flush mounting box
- works with EXTA LIFE system equipment
- range up to 300 m in open areas

**BATTERY-OPERATED  
4-CHANNEL RADIO  
TRANSMITTER  
RNP-22**

**SMART HOME**

exta life

## BATTERY-OPERATED 4-CHANNEL RADIO TRANSMITTER

### **RNP-22**

#### TECHNICAL DATA

Rated supply voltage:	3 V DC
Battery type:	1 x CR2032
Operating range:	max. 300 m in open areas
Transmission:	RF, ISM 868 MHz (868.5 MHz)
Method of transmission with system components:	two-way, 9600 bps
Encryption:	128-bit key algorithm
Channels:	4
Transmission / low battery optical indication:	green LED
Compatible connectors:	monostable (buttons) / bistable (switches)*
Battery life	3-5 years (depending on the frequency of use and operating conditions)
Operating temperature range:	-10 to +55 °C
Enclosure protection rating:	IP20
Dimensions:	47,5 x 47,5 x 13 mm
Weight:	0,03 kg
Reference standards:	PN-ETSI EN 300 220-1, PN-ETSI EN 300 220-2

\* typically, IN1 + IN4 inputs are designed to work with monostable connectors (normally open / bell buttons) – the transmitter sends information upon short triggering of any input. In terms of design, transmitter inputs are suitable for working with bistable connectors (long-lasting application of phase voltage to the transmitter input is possible). However, it is necessary to consider the operation of the transmitter with these kinds of connectors (if possible, the transmitter should be programmed with the receiver in the so-called monostable mode). In this mode, the receiver is turned on as long as the given input is triggered.

**CAUTION!** The transmission range is specified for open areas, which are perfect transmission conditions without obstacles. If the following obstacle types exist between the transmitter and the receiver, expect the transmission range to be reduced by 10 to 40% for brickwork, 5 to 20% for wood and drywall, 40 to 80% for reinforced concrete, 90 to 100% by metal, and 10 to 20% for glass. The transmission range is also adversely affected by overhead and underground high-voltage power lines and GSM transmitter base stations located near the devices.